

Growatt ShineWiFi-X

- Cable free, easy installation
- USB communication port
- Build-in storage, 1 month data
- Online monitoring and maintenance



P O W E R
- I N G O
T O M O -
R R O W O

Growatt
powering tomorrow

www.ginverter.com

Datasheet	ShineWiFi-X
Wireless Parameters	
Wireless standard	802.11 b/g/n
Frequency range	2.4G~2.5G (2412M~2484M)
Transmit power	802.11b: 16±2 dBm (@11Mbps) 802.11g: 14±2 dBm (@54Mbps) 802.11n: 13±2 dBm (@HT20, MCS7)
Receiver sensitivity	CCK, 1 Mbps : -90dBm CCK, 11 Mbps: -85dBm 6 Mbps (1/2 BPSK): -88dBm 54 Mbps (3/4 64-QAM): -70dBm HT20, MCS7 (65 Mbps, 72.2 Mbps): -67dBm
Hardware Parameters	
Data interface	USB
Operation voltage	5V(+/-5%)
Max.power consumption@transmit	1.2W
Display	LED
Application Parameters	
Supported servers	ShineServer
Inverter communication	USB (Modbus RTU protocol)
Server communication	TCP (Modbus TCP protocol)
Max. communication range	50m
Configure type	APP configure
Data transfer interval	5 Minutes
Default server URL	server.growatt.com
General Data	
Dimensions(L/W/H)	135/79/29 mm
Weight	60g
Operating temperature range	-20 °C ~ +65 °C
Warranty	1 year
CE	